

JA Comfort-868



- ✓ manufacturer: Elero
- ✓ built-in 868 MHz two-way radio receiver
- ✓ radio signal routing
- ✓ available powers 6 Nm 9 Nm
- ✓ 0.5 m power cord with Hirschmann plug
- ✓ power supply: 230 V/50 Hz
- ✓ electromagnetic brake
- ✓ slow start, slow approach to end positions
- ✓ regulation of limit positions: electronic
- ✓ continuous operation time: 5 min for the 6 Nm model, 4 min for the 9 Nm model
- ✓ additional safety switch
- ✓ safety class: IP 54
- ✓ power: 115–156 W
- ✓ speed: 26 rpm
- ✓ lamella rotation speed 6 rpm

Elero Ja Comfort 868 drives are intended for facade blinds in new and modernised buildings. They are characterised by high technical advancement such as durability of the gearbox, built-in thermal protection and sealed housing extending the expected time of failure-free operation of the device.

Comfortable use of the drive is ensured by **a silent electromechanical brake and a slow rotation speed enabling precise positioning of the slats.** In this way, you can create exactly the lighting conditions in the interior that its users expect.

Elero JA drives are equipped with electronic limit switches, they are set using a mounting cable or remote control. **The control is carried out using Elero remote controls and transmitters or the NiceSmart control unit.**

The offer includes drives of different power, adapted to the dimensions of the blinds.

ELERO

ELECTRIC DRIVES

WINDOW COVERS